

# PREFORMED LOOP SIZE REFERENCE TABLE

MODEL#	8	8.5	9	9.5	10	11	12
LOOP SIZE	2' X 6'	2.5' X 6'	2' X 7'	3.5' X 6'	2' X 8'	3' X 8'	3' X 9'
	3' X 5'		3' X 6'	2.5' X 7'	3' X 7'	4' X 7'	4' X 8'
	4' X 4'		4' X 5'		4' X 6'	5' X 6'	5' X 7'
				5' X 5'		6' X 6'	
NO. OF TURNS	5	5	5	5	4	4	4

MODEL#	13	14	15	16	17	18	19
LOOP SIZE	3' X 10'	3' X 11'	3' X 12'	4' X 12'	3' X 14'	3' X 15'	3' X 16'
	4' X 9'	4' X 10'	4' X 11'	5' X 11'	5' X 12'	4' X 14'	4' X 15'
	5' X 8'	5' X 9'	5' X 10'	6' X 10'	6' X 11'	6' X 12'	6' X 13'
	6' X 7'	6' X 8'	6' X 9'				
NO. OF TURNS	4	4	4	4	3	3	3

MODEL#	20	21	22	23	24	25	26
LOOP SIZE	3' X 17'	3' X 18'	4' X 18'	4' X 19'	4' X 20'	4' X 21'	4' X 22'
	4' X 16'	6' X 15'	6' X 16'	6' X 17'	6' X 18'	6' X 19'	6' X 20'
	6' X 14'						
NO. OF TURNS	3	3	3	3	3	3	3

MODEL#	28	30	32	34	36	46	56
LOOP SIZE	4' X 24'	4' X 26'	4' X 28'	4' X 30'	4' X 32'	6' X 40'	6' X 50'
	6' X 22'	6' X 24'	6' X 26'	6' X 28'	6' X 30'		
NO. OF TURNS	3	3	3	3	2	2	2

MODEL#	66	76
LOOP SIZE	6' X 60'	6' X 70'
NO. OF TURNS	2	2

The detection height of the Inductive field is considered to be equal to 66% of the shortest side. EXAMPLES:

Loop Size	Height of inductive field
2' X 6'	1.3'
6' X 6'	4.0'
4 X 28	2.6'

*LIS Inc.*

800-964-0711 Fax 800-964-6549